

28 ELECTRICAL SERVICE UNIT

LUBRICATION

1. GENERAL

1.01 This section provides specific lubrication procedures for the 28 electrical service units. It is being reissued to conform to more of a standard format. Since this is a general revision marginal arrows used to indicate changes and additions, have been omitted.

1.02 The figure indicates points to be lubricated and the kind and quantity of lubricant to be used. Lubricate the units prior to placing them in service. After that, lubricate as deemed necessary to provide smooth operation.

1.03 The lubricating symbol in the text of the figure indicates lubrication directions as follows:

- O1 Apply one drop of oil
- O2 Apply two drops of oil
- O3 Apply three drops of oil
- G Apply thin coat of grease
- SAT Saturate (felt oilers, washers, wicks) with oil

1.04 Use TP88970 (KS7470) oil at all locations where the use of oil is indicated. Use TP88973 (KS7471) grease on all surfaces where grease is indicated.

2. LUBRICATION DETAILS

2.01 Stop Magnet

